## Control4<sup>®</sup> DS2 Door Station



## Control4 DS2 Door Station (C4-DS2FM, C4-DS2FMKP, C4-DS2SM, C4-DS2SMKP)

The Control4 DS2 Door Station delivers an amazing audio and HD video intercom experience, enabling customers to monitor and communicate with the front door or their security gate. Combined with Control4 touch screens, customers enjoy greater convenience and peace of mind throughout the home.

- Available in flush-mount and surface-mount options
- Optional integrated keypad is ideal for customers with gates or for those who want to add more security at their doors
- Fast connection speed
- Camera can be viewed outside of an intercom call
- Improved low-light performance
- Motion detection
- Camera snapshots can be emailed to a customer's mobile device
- Dealer-configurable doorbell sounds



## Control4 DS2 Door Station

Model number	C4-DS2FM, C4-DS2FMKP, C4-DS2SM, C4-DS2SMKP
Video	
Camera resolution	1280 × 960 (W×H)
Camera view angle	120° × 90° × 145° (W×H×diagonal)
Camera IR night vision	Yes
Video stream codecs	H.263+, H.263, H.264, MJPEG, MPEG-4
Audio	
Microphone	Yes (integrated)
Speaker	2W
Acoustic pressure	78dB (1 kHz @ 1 meter distance)
Audio stream codecs	G.711, G.729
Interface	
Power	PoE 802.3af (Class 0 - 12.95W)
LAN	10/100Base-TX with Auto-MDIX, RJ-45
Relay outputs	NC/NO contacts, max 30V/1A AC/DC
Active output	8V-12VDC/400mA
Dimensions	
Surface mount	4.21 × 9.21 × 1.10 in. (107 × 234 × 28 mm) (W × H × D)
Flush mount	5.12 × 10.12 × 0.20 in. (130 × 257 × 5 mm) (W×H×thickness protruding from wall)
Mechanical	
Operating temperature	-40°F ~ 140°F (-40°C ~ 60°C)
Storage temperature	-40°F ~ 158°F (-40°C ~ 70°C)
Relative humidity	10% - 95% (non-condensing)
Protection level	IP 54
Accessories	
C4-DS2PLATE-BL	Adapter plate for old Door Station wall box
	Dimensions: 10.24 × 5.12 in. (260 × 130 mm)
C4-DS2BB	Wall box for DS2 Door Station   Dimensions:   • Box: 4.41 × 9.53 × 1.85 in. (112 × 242 × 47 mm)   • Wall cutout: 4.25 × 9.44 in. (108 × 240 mm)

## For information on upgrading an old door station to the DS2 Door Station

Visit ctrl4.co/ds2upgrade



