

Amazing Sound, No Bulky Equipment

Episode® Mini 5.1 AVR

The Episode Mini 5.1 AVR delivers incredible surround sound from a small package, enhancing your listening experience in rooms where space is limited.



Built Small

The Mini 5.1 AVR is perfect for secondary rooms with limited space. Think bedrooms, playrooms, and bonus rooms. It can even hide behind a TV!

Big Power

With 50 watts per front channel, 25 watts per rear channel, and a subwoofer output, this AVR powers up to five speakers and one subwoofer for an immersive audio experience.

The Latest Technology

Equipped with Dolby Digital + DTS 5.1 audio processing and Dolby ProLogic, the Mini 5.1 AVR brings music and movies to life. It also supports HDR, 4K, and 3D viewing.

EPISODE® MINI 5.1 AVR

| EA-MINI-5.1D-200 | |
|--|--|
| | |
| Power requirements | 100-120V/220-240V~50/60 Hz |
| Power consumption | <0.4W (Standby mode) 1.3W (networked Standby mode) Max 300W (Mini 5.1 AVR) |
| Dimensions (L x D x W) (without feet) | 270 × 211 × 44.5 mm (10.63 × 8.31 × 1.75 in.) |
| Weight | Without packaging: 2.25 kg (5.0 lb) With packaging: 3.6 kg (7.9 lb) |
| Audio | |
| Power output @4 ohm | 3 x 50W (FL, C, FR) 2 x 25W (SL,SR) |
| Frequency | 20 Hz to 20 KHz, ±1 dB at 1/8 power @4 ohm |
| Signal-to-noise ratio | >90 dB A-weighted @rated power |
| THD+N | <0.2% 1 KHz @rated power 4 ohm |
| Minimum impedance | 4 ohm |
| Input impedance | 20 kΩ @AUX input |
| Bluetooth | |
| Frequency range | 2402 MHz~2480 MHz |
| Transmitter power | 0-7 dBm |
| Modulation | GFSK, π/4-DQPSK, 8-DPSK |
| Profile | BT 3.0, A2DP v1.2, AVRCPv1.4 |
| HDMI | |
| HDMI | HDMI 2.0 (with audio return channel, 3D 4K, HDR @4K30, deep color) |
| Frequency range | 2402 MHz~2480 MHz |
| HDCP | HDCP 2.2 |













